



Model: **TX750-** (xxx)

Connector Suffix

Radio Models

M06



Motorola GP900, HT1000, XTS2000/ 2250/ 2500/ 3000/ 3500/ XTS5000 / 5300

Speaker Specification:

Type:	Transducer Moving coil dynamic speaker
Impedance:	32 $\Omega \pm 15\%$ @1KHZ
Sensitivity:	92 dB $\pm 10\%$ / 3.5 mW on a coupler
Resonance freq:	4 kHz $\pm 20\%$
Frequency respond:	100 Hz - 4 kHz
Rated input power:	3.5 mW
Maximum input:	500 mW

Microphone Specification:

Type:	Transducer Moving coil dynamic speaker
Sensitivity range:	-64 ± 3 dB
Impedance max:	150 Ω 1 kHz (RL = 2.2 k Ω)
Frequency:	600 Hz ~ 6kHz