



LMR BATTERY SPECIFICATIONS	PART NUMBER
	BP9009

COMPATIBLE RADIOS	Motorola HT750, HT1250, HT1550, PRO5150, PRO7150, PRO9150, GP320, GP340, GP360, GP380, GP640, GP680, GP1280, MTX850, MTX850LS, MTX900, MTX950, MTX8250LS, MTX9250
REPLACES OEM BATTERY	HNN9009AR
COMPATIBLE CHARGER / POD	Endura EC1-MT2, EC1M-MT2, EC2M-MT2-D, EC6M-MT2, EC12M-MT2-D
VOLTAGE	7.5V
CAPACITY	2000 mAh
CHEMISTRY	NiMH
CELL TYPE	FDK HR-4/5AU
OPERATING TEMPERATURE	-10° C to +65° C (discharge) / 0° C to +40° C (charge)
CHARGE CYCLES	500
CHARGE TYPE	Rapid or trickle
CONDITIONER COMPATIBLE	Yes
SHORT CIRCUIT PROTECTION	Yes
HOUSING MATERIAL	ABS
HOUSING SEAL	Ultrasonic weld
METAL WELDING	Pure nickel tabs w/ spot welder
CLIP	Included
WARRANTY	12 months
PRODUCT PHOTO	